

**EXPLODED VIEW**

**GRINDER DOSER  
MINI electronic mod. A**

ESMEDOS05.00 02/2012



MAZZER LUIGI s.r.l  
VIA MOGLIANESE, 113  
30030 GARDIGIANO DI SCORZE' (VE)  
ITALIA  
TEL. +39 041 5830200 r.a. - FAX +39 041 5830060  
E-mail: mazzler@mazzler.com - <http://www.mazzler.com>

N.	DESCRIPTION	CODE	Q.	NOTES
1	Hopper cover	SMI0COD01	1	
2a	Mini Hopper	SMI0CAE03	1	
2b	Mini Hopper 320 gr	SMI0CAE02	1	
3	Hopper locking slide	SMI0SEB01	1	
4	Label "Caution - Hopper"	S000ETA15	1	110V/60Hz versions 100V/50-60Hz versions 220V/60Hz versions
5	Coffee grinding adjustment disk	SSJ0GHA02	1	
6	Label: Coarse-fine / Adjustment initial position	S000ETA03	1	
7	Grinding adjustment disk handle	SSJSPEA04	1	
8	Upper grinding blade holder (low)	SME0POA02	1	
9	Grinding blade set (rif. 189D)	FMA00189D	1	
10	Lower grinding blade holder	SSJ0POA04	1	
11	Super Jolly cover bearing	SSJ0COA01	1	
12	Label "Motor rotation"	S000ETA00	1	
13	Motor cover	SMI0FRA02	1	
14	Bearing 6202 DDU CM	S000CUA07	2	
15	Grinding adjustment spring D1,5	S000MOB14	3	
16	Nipple	S000NIP01	1	
17	"Mazzer 4M" plate	S000TAA02	1	
18	Body for Mini electronic	SME0CAA06	1	
19	"Danger" plate	S000TAA21	1	110V/60Hz versions 100V/50-60Hz versions 220V/60Hz versions
20	Green light switch N/N/V	S000INA12	1	
21	Display connection cable	S000CON04	1	
22	Cable locking D.4-8-11 sp.2 black	S000PAB05	1	
23	Adhesive membrane with display window	S000MEM04	1	
24	Push button holder lid with display window	S000COG02	1	
25	Gasket push button holder lid	S000GUA04	1	
26	Card for push button with display	S000SPU03	1	
27	Ring OR 110.74x1.78 NBR70	S000ANA13	1	
28	Bottom for push button lid	S000FOC00	1	
29	Steel coffee outlet guard	SMI0PRB01	1	
30	Funnel "Mini electronic"	S000IMB08	1	
31	Label "DANGER"	S000ETA14	1	110V/60Hz versions 100V/50-60Hz versions 220V/60Hz versions
32a	Gasket AER Stop + Screen type "A"	S00SGUA01	1	50Hz versions
32b	Gasket AER Stop + Screen type "B"	S00SGUA02	1	60Hz versions
33a	Screen type "A"	S000RET01	1	50Hz versions
33b	Screen type "B"	S000RET02	1	60Hz versions
34	Gasket AER Stop	S000GUA01	1	
35	Fork for filterholder rest "Mini electronic"	S000FOB08	1	
36a	Drip tray (inox)	SMI0PIB03	1	Start from serial number 0832303
36b	Drip tray (plastic)	SMI0PIB02	1	
37	Motor label	-	1	
38	Rotor	SMI0ROA00	1	
39a	Coiled stator single phase 220-240V/50Hz	SMISPAE02	1	220-240V/50Hz versions
39b	Coiled stator single phase 110V/60Hz	SMISPAU02	1	110V/60Hz versions
39c	Coiled stator single phase 220V/60Hz	SMISPAS02	1	220V/60Hz versions
39d	Coiled stator single phase 100V/50-60Hz	SMISPAJ02	1	100V/50-60Hz versions
40	Motor cap	SMI0CAB03	1	
41a	Capacitor locking clamp FR32	S000GRB03	1	Capacitor 6,3 uF
41b	Capacitor locking clamp FR40	S000GRB05	1	Capacitor 20 uF UL
42a	Capacitor 6,3 uF	S000COE17	1	220-240V versions
42b	Capacitor 20 uF UL	S000COE13	1	100-110V versions
43	"External unipotential clamp" plate	S000TAA19	1	CE versions
44	External unipotential clamp	-	1	CE versions
45	Support legs	S00SPIA01	4	
46	Bottom plate for Mini electronic A	SMI0PIEA1	1	
47	Under terminal blocks	S000SOT02	1	12 poles
48	Terminal blocks	S000MOA04	1	12 poles
49	"Ground" plate	S000TAA18	1	
50	Cable locking HSK-K PG11 black	S000PAB15	1	

<b>N.</b>	<b>DESCRIPTION</b>	<b>CODE</b>	<b>Q.</b>	<b>NOTES</b>
51	Plastic spacer H10	S000DIB06	5	
52a	Board for double timer 220-240V el. C	S000SCT06	1	220-240V versions
52b	Board for double timer 100-115V el. C	S000SCT07	1	100-115V versions
53	Nut for cable locking PG11	S000DAA02	1	
54a	Electric cable - "Italy"	S000CAD01	1	
54b	Electric cable - "Europe"	S000CAD04	1	
54c	Electric cable - "USA"	S000CAD05	1	
54d	Electric cable - "Australia"	S000CAD07	1	
54e	Electric cable - "Great Britain"	S000CAD08	1	
54f	Electric cable - "Israel"	S000CAD10	1	
54g	Electric cable - "Switzerland"	S000CAD06	1	
54h	Electric cable - "China"	S000CAD16	1	
54i	Electric cable - "Argentina"	S000CAD18	1	
54j	Electric cable - "Korea"	S000CAD19	1	
54k	Electric cable - "Brazil"	S000CAD20	1	
55	Sheet for Drip Tray locking	SMIOLAM01	1	
56	Push button with display assembly	S00SSPU03	1	
57	Push button holder lid + Adhesive membrane	S00SCOG02	1	

